

RONDA

Lights

Desk

1x Ma-lighting GrandMA3 Full Size

Dimmers

112x MA dimMA channel 2,3kW on Harting16 in grid

8x MA dimMA 2,3kW (4x S.L., 4x S.R.)

Stage roof - Conventional

4x Par64 ACL-set

Stage roof - Intelligent

16x Ayrton Eurus Profile

12x Martin Mac Aura XB

12x Chauvet Strike Array 2

6x Martin Atomic 3000 strobe

4x Martin Mac Aura XB (side lights)

20x Chauvet COLORado PXL Bar 16

Stage floor - Intelligent

6x Ayrton Eurus Profile

6x Martin Mac Aura XB

Stage floor - Conventional

8x Par64 Floorcan

Stage Front Light LX4

6x Ayrton Eurus Profile

6x Martin Mac Aura XB

Frontlight (fixed in catwalk)

8x Robert Juliat profile 15-40deg 2kW

6x Robert Juliat PC-spot 2kW

2x Followspot Robert Juliat Super Korrigan 1,2kW HMI

Houselights (all fixed)

6x Ayrton Eurus Profile

6x Martin Mac Aura XB

35x Colordash Par H7

2x Martin Atomic 3000 Strobe

Haze/fog

1x MDG Me1 + Martin AF-1 MKII

(Warning: this is a very powerful hazer!)

2x Look Viper 2.6 + ADJ DMX Fan

On - stage Power

Stage Left:

1x CEE125A 3ph+N+PE

(Shared with S.R. 125A)

1x CEE63A 3ph+N+PE

1x CEE32A 3ph+N+PE

2x CEE16A 1ph+N+PE

Stage Right:

1x Powerlock 250A 3ph+N+PE

(Shared with house dimmers)

1x CEE125A 3ph+N+PE

(Parallel with 250A Powerlock)

1x CEE125A 3ph+N+PE

(Shared with S.L. 125A)

1x CEE63A 3ph+N+PE

1x CEE32A 3ph+N+PE

2x CEE16A 1ph+N+PE

sACN

All lights are controlled by sACN

Housedesk starts on sACN 1 Priority 100

Guestdesk starts on sACN 1 Priority 200

DMX-Patch Line 1: Conventional - Led

DMX-Patch Line 2: Spot Stage

DMX-Patch Line 3: Spot Stage

DMX-Patch Line 4: Wash Stage

DMX-Patch Line 5: Wash Venue

DMX-Patch Line 6: Spot Venue

DMX-Patch Line 7: Floor / Empty

DMX-Patch Line 8: Led House Light

DMX-Patch Line 9: Free

DMX-Patch Line 10: Free

DMX-Patch Line 11: Free

DMX-Patch Line 12: Free

DMX-Patch Line 13: Led

DMX-Patch Line 14: Led

DMX-Patch Line 15: Led

DMX-Patch Line 16: Led

Lightplot

Separated

Download Information

[LightPlot](#)

[Capture File](#)

[Vectorworks](#)

RONDA

PatchList

sACN 1 - DMX Line 1
Conventional
Housedesk Priority 100

Count on universe:
26x Dimmer Channels
12x Strike Array 2 (2 Channel)

#	Description	Where	Address	Remark
107	ACL-set Par64	LX1 Outside	49	
108	ACL-set Par64	LX1 Inside	50	
109	ACL-set Par64	LX2 Outside	7	
110	ACL-set Par64	LX2 Inside	8	
111	Robert Juliat 15-40 2kW	Catwalk	76	
112	Robert Juliat 15-40 2kW	Catwalk	77	
113	Robert Juliat 15-40 2kW	Catwalk	78	
114	Robert Juliat 15-40 2kW	Catwalk	79	
115	Robert Juliat 15-40 2kW	Catwalk	80	
116	Robert Juliat 15-40 2kW	Catwalk	81	
117	Robert Juliat 15-40 2kW	Catwalk	82	
118	Robert Juliat 15-40 2kW	Catwalk	83	
119	Robert Juliat PC 2kW	Catwalk	84	
120	Robert Juliat PC 2kW	Catwalk	85	
121	Robert Juliat PC 2kW	Catwalk	86	
122	Robert Juliat PC 2kW	Catwalk	87	
123	Robert Juliat PC 2kW	Catwalk	88	
124	Robert Juliat PC 2kW	Catwalk	89	
125 t/m 128	4x Floor-channels	Stage Right	97 t/m 100	2,3kW
129 t/m 132	4x Floor-channels	Stage Left	101 t/m 104	2,3kW
401	Chauvet Strike Array 2	LX1	201	2 Channel Mode
402	Chauvet Strike Array 2	LX1	203	2 Channel Mode
403	Chauvet Strike Array 2	LX1	205	2 Channel Mode
404	Chauvet Strike Array 2	LX1	207	2 Channel Mode
405	Chauvet Strike Array 2	LX2	209	2 Channel Mode
406	Chauvet Strike Array 2	LX2	211	2 Channel Mode
407	Chauvet Strike Array 2	LX2	213	2 Channel Mode
408	Chauvet Strike Array 2	LX2	215	2 Channel Mode
409	Chauvet Strike Array 2	LX3	217	2 Channel Mode
410	Chauvet Strike Array 2	LX3	219	2 Channel Mode
411	Chauvet Strike Array 2	LX3	221	2 Channel Mode
412	Chauvet Strike Array 2	LX3	223	2 Channel Mode
	Free DMX Channels		105 t/m 200	
	Free DMX Channels		225 t/m 512	

sACN 2 - DMX Line 2
Spot Stage
Housedesk Priority 100

Count on universe:
12x Eurus Profile (Standard Mode)

#	Description	Where	Address	Remark
1	Ayrton Eurus Profile	LX1	1	Standard Mode
2	Ayrton Eurus Profile	LX1	42	Standard Mode
3	Ayrton Eurus Profile	LX1	83	Standard Mode
4	Ayrton Eurus Profile	LX1	124	Standard Mode
5	Ayrton Eurus Profile	LX1	165	Standard Mode
6	Ayrton Eurus Profile	LX1	206	Standard Mode
7	Ayrton Eurus Profile	LX2	247	Standard Mode
8	Ayrton Eurus Profile	LX2	288	Standard Mode
9	Ayrton Eurus Profile	LX2	329	Standard Mode
10	Ayrton Eurus Profile	LX2	370	Standard Mode
11	Ayrton Eurus Profile	LX2	411	Standard Mode
12	Ayrton Eurus Profile	LX2	452	Standard Mode
	Free DMX Channels		493 t/m 512	

sACN 3 - DMX Line 3
Spot Stage
Housedesk Priority 100

Count on universe:
10x Eurus Profile (Standard Mode)
6x Atomic 3000 (4Channel Mode)

#	Description	Where	Address	Remark
13	Ayrton Eurus Profile	LX3	1	Standard Mode
14	Ayrton Eurus Profile	LX3	42	Standard Mode
15	Ayrton Eurus Profile	LX3	83	Standard Mode
16	Ayrton Eurus Profile	LX3	124	Standard Mode
17	Ayrton Eurus Profile	LX4	165	Standard Mode
18	Ayrton Eurus Profile	LX4	206	Standard Mode
19	Ayrton Eurus Profile	LX4	247	Standard Mode
20	Ayrton Eurus Profile	LX4	288	Standard Mode
21	Ayrton Eurus Profile	LX4	329	Standard Mode
22	Ayrton Eurus Profile	LX4	370	Standard Mode
81	Martin Atomic 3000 DMX	LX1	411	4 Channel Mode
82	Martin Atomic 3000 DMX	LX1	415	4 Channel Mode
83	Martin Atomic 3000 DMX	LX1	419	4 Channel Mode
84	Martin Atomic 3000 DMX	LX2	423	4 Channel Mode
85	Martin Atomic 3000 DMX	LX2	427	4 Channel Mode
86	Martin Atomic 3000 DMX	LX3	431	4 Channel Mode
	Free DMX Channels		435 t/m 512	

sACN 4 - DMX Line 4
Wash Stage & Side Wash
Housedesk Priority 100

Count on universe:
16x Aura XB (Extended Mode)

#	Description	Where	Address	Remark
41	Martin Mac Aura XB	LX1	1	Extended Mode
42	Martin Mac Aura XB	LX1	26	Extended Mode
43	Martin Mac Aura XB	LX1	51	Extended Mode
44	Martin Mac Aura XB	LX1	76	Extended Mode
45	Martin Mac Aura XB	LX1	101	Extended Mode
46	Martin Mac Aura XB	LX1	126	Extended Mode
47	Martin Mac Aura XB	LX2	151	Extended Mode
48	Martin Mac Aura XB	LX2	176	Extended Mode
49	Martin Mac Aura XB	LX2	201	Extended Mode
50	Martin Mac Aura XB	LX2	226	Extended Mode
51	Martin Mac Aura XB	LX2	251	Extended Mode
52	Martin Mac Aura XB	LX2	276	Extended Mode
53	Martin Mac Aura XB	Downrigger SR	301	Extended Mode
54	Martin Mac Aura XB	Downrigger SR	326	Extended Mode
55	Martin Mac Aura XB	Downrigger SL	351	Extended Mode
56	Martin Mac Aura XB	Downrigger SL	376	Extended Mode
	Free DMX Channels		401 t/m 512	

sACN 5 - DMX Line 5
Wash Venue
Housedesk Priority 100

Count on universe:
12x Aura XB (Extended Mode)

#	Description	Where	Address	Remark
57	Martin Mac Aura XB	LX3	1	Extended Mode
58	Martin Mac Aura XB	LX3	26	Extended Mode
59	Martin Mac Aura XB	LX3	51	Extended Mode
60	Martin Mac Aura XB	LX3	76	Extended Mode
61	Martin Mac Aura XB	LX3	101	Extended Mode
62	Martin Mac Aura XB	LX3	126	Extended Mode
63	Martin Mac Aura XB	Venue Truss SR	151	Extended Mode
64	Martin Mac Aura XB	Venue Truss MID	176	Extended Mode
65	Martin Mac Aura XB	Venue Truss MID	201	Extended Mode
66	Martin Mac Aura XB	Venue Truss MID	226	Extended Mode
67	Martin Mac Aura XB	Venue Truss MID	251	Extended Mode
68	Martin Mac Aura XB	Venue Truss SL	276	Extended Mode
	Free DMX Channels		301 t/m 512	

sACN 6 - DMX Line 6
Spot Venue
Housedesk Priority 100

Count on universe:
6x Eurus Profile (standard Mode)
2x Atomic 3000 (4Channel Mode)

#	Description	Where	Address	Remark
23	Ayrton Eurus Profile	Venue Truss SR	1	Standard Mode
24	Ayrton Eurus Profile	Venue Truss SR	42	Standard Mode
25	Ayrton Eurus Profile	Venue Truss MID	83	Standard Mode
26	Ayrton Eurus Profile	Venue Truss MID	124	Standard Mode
27	Ayrton Eurus Profile	Venue Truss SL	165	Standard Mode
28	Ayrton Eurus Profile	Venue Truss SL	206	Standard Mode
87	Martin Atomic 3000 DMX	Venue Truss SR	247	4 Channel Mode
88	Martin Atomic 3000 DMX	Venue Truss SL	251	4 Channel Mode
	Free DMX Channels		255 t/m 512	

sACN 7 - DMX Line 7
Spot + Wash Floor
Housedesk Priority 100

Count on universe:
6x Eurus Profile (standard Mode)
6x Aura XB (Extended Mode)
Free Universe To Use If you don't use the floor package

#	Description	Where	Address	Remark
29	Ayrton Eurus Profile	Floor	1	Standard Mode
30	Ayrton Eurus Profile	Floor	42	Standard Mode
31	Ayrton Eurus Profile	Floor	83	Standard Mode
32	Ayrton Eurus Profile	Floor	124	Standard Mode
33	Ayrton Eurus Profile	Floor	165	Standard Mode
34	Ayrton Eurus Profile	Floor	206	Standard Mode
69	Martin Mac Aura XB	Floor	247	Extended Mode
70	Martin Mac Aura XB	Floor	272	Extended Mode
71	Martin Mac Aura XB	Floor	297	Extended Mode
72	Martin Mac Aura XB	Floor	322	Extended Mode
73	Martin Mac Aura XB	Floor	347	Extended Mode
74	Martin Mac Aura XB	Floor	372	Extended Mode
	Free DMX Channels		397 t/m 505	
201	MDG Me1 Hazer	Stage Floor	508	3 Channel Mode
202	Martin AF1 MK II	In Hazer Case	511	1 Channel Mode
203	Look Viper 2.6	Stage Floor	506	1 Channel Mode
204	Look Viper 2.6	Stage Floor	507	1 Channel Mode
205	ADJ DMX Fan	In Smoke Case	512	1 Channel Mode
206	ADJ DMX Fan	In Smoke Case	512	1 Channel Mode

sACN 8 - DMX Lijn 8
House Light
Housedesk Priority 100

35x Colordash Par H7 (8Channels)

#	Description	Where	Address	Remark
301	Colordash Par H7	Hall Under Balcony	151	8 Channels
302	Colordash Par H7	Hall Under Balcony	159	8 Channels
303	Colordash Par H7	Hall Under Balcony	167	8 Channels
304	Colordash Par H7	Hall Under Balcony	175	8 Channels
305	Colordash Par H7	Hall Under Balcony	183	8 Channels
306	Colordash Par H7	Hall Under Balcony	191	8 Channels
307	Colordash Par H7	Hall Under Balcony	199	8 Channels
308	Colordash Par H7	Hall Under Balcony	207	8 Channels
309	Colordash Par H7	Hall Under Balcony	215	8 Channels
310	Colordash Par H7	Hall Under Balcony	223	8 Channels
311	Colordash Par H7	Hall Under Balcony	231	8 Channels
312	Colordash Par H7	Hall Under Balcony	239	8 Channels
313	Colordash Par H7	Hall Under Balcony	247	8 Channels
314	Colordash Par H7	Hall Under Balcony	255	8 Channels
315	Colordash Par H7	Hall Under Balcony	263	8 Channels
316	Colordash Par H7	Hall Under Balcony	271	8 Channels
317	Colordash Par H7	Hall Stairs	279	8 Channels
318	Colordash Par H7	Hall Stairs	287	8 Channels
319	Colordash Par H7	Hall Stairs	295	8 Channels
320	Colordash Par H7	Hall Balcony	303	8 Channels
321	Colordash Par H7	Hall Balcony	311	8 Channels
322	Colordash Par H7	Hall Balcony	319	8 Channels
323	Colordash Par H7	Hall Balcony	327	8 Channels
324	Colordash Par H7	Hall Balcony	335	8 Channels
325	Colordash Par H7	Hall Balcony	343	8 Channels
326	Colordash Par H7	Hall Balcony	351	8 Channels
327	Colordash Par H7	Hall Balcony	359	8 Channels
328	Colordash Par H7	Hall Balcony	367	8 Channels
329	Colordash Par H7	Hall Balcony	375	8 Channels
330	Colordash Par H7	Hall Balcony	383	8 Channels
331	Colordash Par H7	Hall Balcony	391	8 Channels
332	Colordash Par H7	Hall Balcony	399	8 Channels
333	Colordash Par H7	Hall Stairs	407	8 Channels
334	Colordash Par H7	Hall Stairs	415	8 Channels
335	Colordash Par H7	Hall Stairs	423	8 Channels
	Free DMX Channels		431 t/m 512	

sACN 13 - DMX Lijn 13 **6x COLORado PXL Bar 16 (84Channels)**
House Light
Housedesk Priority 100

#	Description	Where	Address	Remark
501	Chauvet COLORado PXL Bar 16	LX1	1	Standard 84Channels
502	Chauvet COLORado PXL Bar 16	LX1	85	Standard 84Channels
503	Chauvet COLORado PXL Bar 16	LX1	169	Standard 84Channels
504	Chauvet COLORado PXL Bar 16	LX1	253	Standard 84Channels
505	Chauvet COLORado PXL Bar 16	LX1	337	Standard 84Channels
506	Chauvet COLORado PXL Bar 16	LX1	421	Standard 84Channels

sACN 14 - DMX Lijn 14 **6x COLORado PXL Bar 16 (84Channels)**
House Light
Housedesk Priority 100

#	Description	Where	Address	Remark
507	Chauvet COLORado PXL Bar 16	LX1	1	Standard 84Channels
508	Chauvet COLORado PXL Bar 16	LX1	85	Standard 84Channels
509	Chauvet COLORado PXL Bar 16	LX1	169	Standard 84Channels
510	Chauvet COLORado PXL Bar 16	LX1	253	Standard 84Channels
511	Chauvet COLORado PXL Bar 16	LX2	337	Standard 84Channels
512	Chauvet COLORado PXL Bar 16	LX2	421	Standard 84Channels

sACN 15 - DMX Lijn 15 **6x COLORado PXL Bar 16 (84Channels)**
House Light
Housedesk Priority 100

#	Description	Where	Address	Remark
513	Chauvet COLORado PXL Bar 16	LX2	1	Standard 84Channels
514	Chauvet COLORado PXL Bar 16	LX2	85	Standard 84Channels
515	Chauvet COLORado PXL Bar 16	LX2	169	Standard 84Channels
516	Chauvet COLORado PXL Bar 16	LX2	253	Standard 84Channels
517	Chauvet COLORado PXL Bar 16	LX2	337	Standard 84Channels
518	Chauvet COLORado PXL Bar 16	LX2	421	Standard 84Channels

sACN 16 - DMX Lijn 16 **2x COLORado PXL Bar 16 (84Channels)**
House Light
Housedesk Priority 100

#	Description	Where	Address	Remark
519	Chauvet COLORado PXL Bar 16	LX2	1	Standard 84Channels
520	Chauvet COLORado PXL Bar 16	LX2	85	Standard 84Channels

sACN9 t/m 12 - DMX Line 9 t/m 12 On the Luminode 12
 Free Line
 Housedesk Priority 100

#	Description	Where	Address	Remark
	Free			Free Universe To Use

IP-Adresses Light Network Ronda

Equipment	MA-Net	IP Adress
GMA3 Full Size	192.168.168.201	10.98.168.201
NDP 1	192.168.168.202	
NDP 2	192.168.168.203	
LumiNode 12		10.98.168.211
Luminex GigaCore 16T		10.98.168.212
Pharos Control LPC 4		10.98.168.215
Pharos Control TCP 5		10.98.168.216